

STOP

MODEL 555

12-60

12 Volt Hybrid Auto Radio Tubes that Require 12 Volts "B" Supply Cannot be Tested on this Tester.

0A2	22	2	33	147	S	5	1	5
0A3	15	2	31		S	5	1	5
0A4		1	37		S	5	4	5
0B2	17	2	19	457	S	1	1	1
0B3	17	2	36		S	5	1	5
0C3	18	2	35		S	5	1	5
0D3	22	2	30		S	5	1	5
0Z4-P 1		1	43		S	3-5	4	3
0Z4-P 2		1	43				4	5
1AB5	4	1	32	8	S	2-3-6	2	236
1AD4	3	5	0		S	1-2-4	3	124
1AE4	3	1	38	5	S	2-3-6	1	236
1AF4	4	1	32	5	S	2-3-6	2	236
1AF4-PEN	4	1	25		S	3-4-5-6	2	456
1AF5-DIO	4	1	0				3	3
1AG4	3	5	33		S	4-6-7	2	467
1AH4	3	3	33		S	4-6-7	2	467
1AJ5-PEN	3	4	25		S	3-5-6-7	2	367
1AJ5-DIO	3	4	45				4	5
1AX2	4	2	0	58	S	C	4	C
1B3/8016	4	2	20		S	C	4	C
1C21	13	2	35		S	5-7	1	57
1DN5-PEN	4	1	25	5	S	2-3-4-6	2	236
1DN5-DIO	4	1	0				2	4
1G3	4	2	22		S	C	4	C
1H2	4	2	10		S	C	4	C
1J3	4	2	5		S	C	4	C
1J5	5	2	30		S	3-4-5	2	345
1K3	4	2	5		S	C	4	C
1LA4	4	1	31		S	2-3-6	2	236
1LA6	4	1	29		S	2-3-4-5-6	2	23456
1LB4	4	1	31		S	2-3-6	2	236
1LC5	4	1	32		S	2-3-4-6	2	2346
1LC6	4	1	29		S	2-3-4-5-6	2	23456
1LD5-PEN	4	1	32		S	2-3-4-6	2	236
1LD5-DIO	4	1	0				3	4
1LE3	4	1	32		S	2-6	2	26
1LG5	4	1	33		S	2-3-4-6	2	2346
1LH4-TRI	4	1	31		S	2-4-6	2	26
1LH4-DIO	4	1	0				3	4
1LN5	4	1	32		S	2-3-4-6	2	2346
1N2	4	2	20		S	C	4	C
1N5	4	2	33		S	C-3-4	2	C34
16N-PEN	4	2	30		S	3-4-5-6	2	345
1N6-DIO	4	2	0				3	6
1R5	4	1	32	5	S	2-3-4-6	2	2346
1S2	4	2	25		S	C	4	C
1S4	4	5	35	16	S	2-3-4	2	234
1S5-PEN	4	1	28		S	3-4-5-6	2	456
1S5-DIO	4	1	0				3	3
1S6-PEN	3	5	0		S	1-3-6-8	3	138
1S6-DIO	3	5	10				3	6

